

LEROY SOMER
STAMFORD

Image for illustration purposes only

IPG800 GENSET

Generating Set Powered By  Perkins

Output Ratings

Generating Set Model	Prime Power	Standby Power
1500rpm, 50 Hz / 400V	640KWe / 800KVA	720KWe / 900KVA
1800rpm, 60 Hz / 440V	675KWe / 844KVA	750KWe / 938KVA

Genset Specifications

Engine Make & Model	Perkins 4006-23TAG3A		
Origin	UK		
Alternator Type	HCI634G		
Control Panel	Digital deap sea		
Circuit Breaker Type	3 Pole MCCB		
Tropical Cooling System			
Digital Electronic Governor			
Turbocharged			
Exceptional Power to Weight Ratio			
Fuel System	50%	75%	100%
1500rpm, 50 Hz	88	132	175
1800rpm, 60Hz	96	144	200

*Prime Power (l/hr)

Engine Technical Data


No. of Cylinders / Alignment	6 In Line
Cycle	4 Stroke
Aspiration	Turbocharged
Injection	Direct
Bore, mm	160
Stroke, mm	190
Displacement, l	22.9
Compression Ratio	13.6:1
Starting	24V Electric
Alternators, Amps	24V/70A

Alternator Technical Data

No. of Bearings	Single Bearing
Insulation System	Class H
Excitation	PMG
Voltage Regulator	MX321
Protection	IP23
Temperature Rise, °C	125
Regulation	±0.5%
No. of Phases	3
No. of Poles	4

Dimensions & Weight

Length(m)	Width(m)	Height(m)	Weight(kg)	Tank Capacity(L)
4.40	1.80	2.30	6300	N/A



RATING GUIDELINES

PRIME POWER rating corresponds to ISO Standard Power for continuous operation. It is applicable for supplying electrical power at variable load for an unlimited number of hours instead of commercially purchased power. A10% overload capability for governing purpose is available for this rating.

MAXIMUM STANDBY POWER rating corresponds to ISO Standard Fuel Stop Power. It is applicable for supplying standby electrical power at variable load in areas with well established electrical networks in the event of normal utility power failure. No overload capability is available for this rating. **1 hp = 1 kW x 1.36**

IPG800 GENSET

Generating Set Powered By  Perkins

**LEROY
SOMER**

STAMFORD

Performances	1500rpm	1800rpm
Alternator Efficiency	94.4%	94.5%
Engine Power		
Prime Power, KWm(hp)	679(910)	715(959)
Standby Power, KWm(hp)	760(1019)	795(1066)
Alternator		
Prime Power, KWe	648	740

Lubrication System	1500rpm	1800rpm
Oil Consumption (l/hr)	0.25% of fuel consumption	
Oil Sump Capacity, l	-	
Oil System Capacity Include Filters, l	113.4	

Cooling System	1500rpm	1800rpm
Heat Radiation from Engine and Alternator, Power KW	86	90
Heat Rejection to Coolant and Lube Oil at Standby Power, KW	315	330
Radiator Cooling Air Flow, m ³ /min (cfm)	1200(42976.8)	1320(46614.48)
Coolant Capacity, l	105	

Intake & Exhaust System	1500rpm	1800rpm
Air Flow Combustion at Standby Power, m ³ /min(cfm)	73(2578)	78(2554)
Heat Rejection Exhaust at Standby Power, KW	741	759
Exhaust Gas Temperature at Standby °C	500	500
Max Allowable Back Pressure in Exhaust Line, Kpa	6.0	6.0
Exhaust Gas Flow at Standby Power, m ³ /min(cfm)	193(6815)	209(7380)

Accessories	
Stainless Steel Flexible	Anti-Vibration Pads
Standard Silencer	Battery Disconnect Switch

Control Panel Readings
<ul style="list-style-type: none"> • AC volts, AC currents, DC volts, frequency, rpm, hour counter, power factor. • Low oil pressure, high water temperature, boost pressure and temperature, KW, kWh, KVA, KVAR, fuel consumption, relative load • Oil pressure, water temperature, low oil level, high oil temperature • DC alternator failure, over speed, over crank (Fail to start), over under voltage, over under current, any sensor failure • Low coolant level - Configurable inputs & outputs • Upgradable for GSM network connection, Signal SMS messages.

Optional Equipment
<ul style="list-style-type: none"> • Engine <ul style="list-style-type: none"> -Coolant heater -Oversize batteries -Extra fuel pre-filter water separator • Alternator <ul style="list-style-type: none"> -12 wire reconnectable stator/terminal arrangement -Upgrade to AVR MX321 -Quadrature droop kit -Anti-condensation heater -Air inlet filters • General <ul style="list-style-type: none"> -Upgrade to modular controller for paralleling -Upgrade to ACB -Battery charger -Automatic transfer switch -Fuel level switch High / Low for alarm and control -Fuel transfer pump Automatic / Manual -Residential grade silencer -Weather protective and acoustic enclosure.

Spare Parts Kit (Optional)	Genuine - Perkins
Oil filter, full flow	(3)
Fuel filter	(1)
Air filter	(2)
Fan belt set	(1)
Alternator belt set	(1)

General Information
Documentation
Engine instruction book-English
Alternator manual- English
Wiring diagram

Warranty
One year or 1000 thousand hours whichever elapsed first against all defects in material / or workmanship, subject to the terms and conditions of the Manufacturer's warranty.

IMG HEAD OFFICES
 IMG Bldg, Mazraa area Beirut-Lebanon
 Phone: +961 (1) 311737 Mobile: +961 (03) 059 995
 Website: www.img-lb.com